



A4-8

Live-Performance Studio Monitor with 4 Channels, Mixer, Effects, and Bluetooth®

Elite Acoustics' A4-8 Live-Performance Studio Monitor with Mixer, Effects, and Bluetooth features: 4 input channels and integrated Digital Effects with an efficient Class D bi-amp driving an 8 inch woofer and 1 inch silk-dome tweeter to deliver maximum clarity. The Mastering section contains a 3-band EQ, Master Volume and stereo AUX input with level control. Switchable Direct Out or line-level monitoring outputs are provided for daisy chaining to additional powered speakers. A4-8 preserves the stereo outputs thereby allowing true stereo playback when integrated with additional speakers. The cabinet is constructed from solid MDF to ensure durability and high fidelity sound, and contains an integrated pole-cup. A4-8 utilizes a metal chassis with panel-mounted POTs/Jacks. The included charger doubles as a power supply for non-battery powered operation. A4-8 can also be powered and charged from a car (charger included) and once fully charged, the speaker can provide over 10 hours of playing time. Built-in overcharge/over-drain circuits protect the battery to maximize battery life. Designed and assembled in USA.

Input & Output Connectors							
Nominal Output Level (1kHz)	Stereo Inputs	Channel 1 & 2	Channel 3/4	Auxiliary In Jack	Main & Direct Outputs	EFX Bypass & CHAN 1/2 Mute	Power
Right Channel Link Out : -10 dBu Main/Direct Output : +4 dBu	1/4" Left/Right Input	One XLR, One 1/4" TRS	Two 1/4" TRS	1/8"	One 1/4" TRS Two XLR(Left/Right)	One 1/4" TRS One 1/4" TRS	DC Jack In

Specifications									
Woofer	Tweeter	Amplifier	Power	Power Supply	Current Draw	Frequency Response	Built-In Pole-Mount	Dimension	Weight
8"	1"	Class D Bi-AMP	40W	DC 12V	2000 mA	40Hz-22kHz (+/-3dB)	35mm Receptacle On Bottom Of Unit	10.90"L x 10.25"W x 16.40"H	28 lbs.

Controls					
Power Switch	Master Indicators	Auxiliary In	Channel 1 & Channel 2	Channel 3/4	Master
Yes	Signal Clip and Power	Level Knob	Gain, Mute, EFX Send Level EQ, Phase, Notch Filter, Frequency	Level Knob & EFX Send Level	Volume Knob & Equalizer (Low Freq Knob, Mid Freq Knob, High Freq Knob), Effect Mix, Decay/Rate, Effects Program Select

Other Features						
Rechargeable Battery w/ Meter	Battery Switch	Bluetooth	USB	Front Ports	Magnetic Shielding	Accessories
Up to 8 Hours Play Time	Slide Switch	Yes	Charging Only	Optimized For Extended Low-Frequency Response	Eliminates Interference With Other Electronic Equipment	AC Cord, AC Adaptor, DC Cord For The Car, Owner's Manual

*Not Included on Channel 2.
 **Due to continuous development & improvements of our products, features specifications are subject to change without notice. All weights & measures are approximate.